

# Auto Start Generator Control Panel



## ENGINE & GENERATOR CONTROLS

### P9 SERIES

#### STANDARD FEATURES

Dimensions: 15.31ö (w) x 11.12ö (h) x 10.75ö (d)

ABS UV protected corrosion proof cabinet and corrosion resistant hardware.

Built around the MEC20 Genset controller with CSA certification to UL & CSA standards. Also meets NFPA110 requirements. Controller is user-programmable via front-panel display only.

LCD display mounted on weatherproof lexan faceplate

Datcon oil pressure and coolant temperature sender (programmable warning and shutdown points) included.

Wired fuel relay, auxiliary relay, and start solenoid included.

Magnetic pickup sensor (speed sensing via magnetic pickup only) included.

Panel Includes: current transformers, vibration isolators, operations manual, and wiring schematics.



P9                      
 1            2            3            4

#### OPTIONAL MODULES

	1. Voltage	3. PH/FRQ
	A = 480 B = 380 C = 240	A = 1/60
EAP 110 Annunciator *	D = 220 E = 208 F = 120	B = 1/50
		C = 3/60
Dry contact expansion module *	2. Amps (Example)	D = 3/50
	(Format= amps/10)	
* (Both meet NFPA110 requirements)	005 = 50 amp	4. DC Volt
	010 = 100 amp	1 = 12
	015 = 150 amp	2 = 24
	150 = 1500 amp	

#### PART NUMBER KEY

National Marketing and Distribution by Davidson Sales Co.

839 Bill France Blvd., Daytona Beach, FL 32117

Phone: (386)274-2079 Fax: (386)274-2279 www.davidsonsales.com