


Generator Control Panel

Panelsource

ENGINE & GENERATOR CONTROLS

P1, P2, AND P3 SERIES



P2

7" (w) x 7" (h) x 7" (d)
(2.70" panelboard style meters)



P1 & P3

P1: 11" (w) x 3.6" (h) x 8" (d)
(2.70" panelboard style meters)

P3: 15" (w) x 4.5" (h) x 7.5" (d)
(3.5" panelboard style meters)

STANDARD FEATURES

- ABS UV protected corrosion proof cabinet and corrosion resistant hardware.
- 2% accuracy ammeter, voltmeter and frequency meters with required fusing
- Volt/Amps phase selector switch
- Panel Includes: current transformers, vibration isolators, and wiring schematics.

P1,2,3 1 2 3

1. Voltage

A = 480 C = 240 - 208

2. Amps (Example)

(Format= amps/10)

005 = 50 amp

010 = 100 amp

015 = 150 amp

150 = 1500 amp

3. PH/FRQ

A = 1/60

B = 1/50

C = 3/60

D = 3/50

PART NUMBER KEY

National Marketing and Distribution by Davidson Sales Co.

839 Bill France Blvd., Daytona Beach, FL 32117

Phone: (386)274-2079 Fax: (386)274-2279 www.davidsonsales.com