

Generator Control Panel

Panelsource

ENGINE & GENERATOR CONTROLS

P4 SERIES



STANDARD FEATURES

- Dimensions: 14" (w) x 7.5" (h) x 10" (d)
- ABS corrosion proof cabinet
- 3 1/2" 2% accuracy ammeter, voltmeter and frequency meters with required fusing
- Cabinet supplied with 3 gauge holes and hourmeter square hole for customer mounted gauges or optional gauge package.
- Current transformers
- Volt/Amps phase selector switch
- Vibration isolators
- Corrosion resistant hardware
- Wiring diagrams

P4
1 2 3 4

1. Voltage

A = 480 C = 240 - 208
F = 120

2. Amps (Example)

(Format= amps/10)
006 = 60amp
010 = 100 amp
015 = 150 amp
150 = 1500 amp

3. PH/FRQ

A = 1/60
B = 1/50
C = 3/60
D = 3/50

4. DC Volt (with gauge pack option)

1 = 12
2 = 24

PART NUMBER KEY

National Marketing and Distribution by Davidson Sales Co.

P.O. Box 9086, Daytona Beach, FL 32120

Phone: (386)274-2079 Fax: (386)274-2279 www.davidsonsales.com