

Generator Control Panel



ENGINE & GENERATOR CONTROLS

P4 SERIES

STANDARD FEATURES

- Dimensions: 14" (w) x 7.5" (h) x 10" (d)
- ABS UV protected corrosion proof cabinet and corrosion resistant hardware.
- 3.5" 2% accuracy ammeter, voltmeter and frequency meters with required fusing
- Volt/Amps phase selector switch
- Cabinet supplied with 3 gauge holes (2-1/16") and hourmeter square hole (1.42" x .92") for customer mounted gauges or optional gauge package.
- Panel Includes: Current transformers, vibration isolators, and wiring schematics.



P4 with VDO gauge pack option shown

P4
 1 2 3 4

1. Voltage

A = 480 C = 240 - 208

2. Amps (Example)

(Format= amps/10)

- 005 = 50 amp
- 010 = 100 amp
- 015 = 150 amp
- 150 = 1500 amp

3. PH/FRQ

- A = 1/60
- B = 1/50
- C = 3/60
- D = 3/50

4. DC Volt (with gauge pack option)

- 1 = 12
- 2 = 24

PART NUMBER KEY

National Marketing and Distribution by Davidson Sales Co.

839 Bill France Blvd., Daytona Beach, FL 32117
 Phone: (386)274-2079 Fax: (386)274-2279 www.davidsonsales.com