

Generator Control Panel



ENGINE & GENERATOR CONTROLS

P4 SERIES



P4 with VDO gauge pack option shown

STANDARD FEATURES

- Dimensions: 15.37" (w) x 8.5" (h) x 10.25" (d)
- ABS UV protected corrosion proof cabinet and corrosion resistant hardware.
- 3.5" 2% accuracy ammeter, voltmeter and frequency meters with required fusing
- Volt/Amps phase selector switch
- Cabinet supplied with 3 gauge holes (2-1/16") and hourmeter square hole (1.42" x .92") for customer mounted gauges or optional gauge package.
- Panel Includes: Current transformers, vibration isolators, and wiring schematics.

- P4
- 1 2 3 4
1. Voltage
A = 480 C = 240 - 208
 2. Amps (Example)
(Format= amps/10)
005 = 50 amp
010 = 100 amp
015 = 150 amp
150 = 1500 amp
 3. PH/FRQ
A = 1/60
B = 1/50
C = 3/60
D = 3/50
 4. DC Volt (with gauge pack option)
1 = 12
2 = 24

PART NUMBER KEY

National Marketing and Distribution by Davidson Sales Co.

839 Bill France Blvd., Daytona Beach, FL 32117
 Phone: (386)274-2079 Fax: (386)274-2279 www.davidsonsales.com