

# Auto Start Generator Control Panel



## ENGINE & GENERATOR CONTROLS

### P8X163 SERIES

#### STANDARD FEATURES

- Dimensions: 10" (w) x 7" (h) x 7" (d)
- ABS UV protected corrosion proof cabinet and corrosion resistant hardware.
- 2% accuracy voltmeter with required fusing
- Engine control switch (manual-off-auto)
- ECU-9910 automatic start engine controller with: automatic cycle cranking, low oil pressure safety shutdown, high water temperature safety shutdown, overspeed safety shutdown, overcrank safety shutdown, loss of speed signal detection, programmable timer for preheat applications
- Premium VDO engine gauge package: oil pressure gauge, coolant temperature gauge, engine hourmeter and sender/switch combination
- Wired fuel, start and glow plug relays
- Magnetic pickup sensor (speed detection via magnetic pickup only except, ECU-9907) included.
- Panel Includes: vibration isolators, operations manual, and wiring schematics.



Metering/Wiring/Fusing up to 480 volt ■

Wiring for 12 VDC or 24 VDC system ■  
(optional ECU-9988N w/ annunciator outputs, ECU-9988L and ECU-9907 (generator AC freq. speed sensing)

#### OPTIONAL FEATURES

National Marketing and Distribution by Davidson Sales Co.

839 Bill France Blvd., Daytona Beach, FL 32117

Phone: (386)274-2079 Fax: (386)274-2279 www.davidsonsales.com